

Ultra-Fast Recovery Diodes 8A FRED

Features

- Adopt FRED chip
- Low forward Voltage drop
- Fast reverse recovery time
- High frequency operation
- High purity , high temperature epoxy encapsulation for enhanced mechanical strength and moisture resistance
- Guard ring for enhanced ruggedness and long term reliability

Typical Applications

Typical applications are in switching power supplies , converter freewheeling diodes , and reverse battery protection.

Mechanical Data

- Package:** ITO-220AC
Molding compound meets UL 94 V-0 flammability rating , RoHS-compliant
Terminals: Tin plated leads , solderable per J -STD-

	stg	†	-55 ~ +175
Junction Temperature	T _j	†	-55 ~ +175
Typical Junction capacitance @4V, 1MHz	C _j	pF	40

Mounting torque

```
'@recommand10@que' " " " " " " " " " " " " " " " " M
```



MUR860F

Electrical Characteristics

PARAMETER		UNIT	TEST CONDITIONS		Min	Typ	Max
Instantaneous forward voltage drop per diode	$I_{FM} V$	V	$I_{FM} = 8.0A @ T_j = 25$		-	1.40	1.6
			$I_{FM} = 8.0A @ T_j = 150$		-	1.15	1.3
DC reverse current at rated DC blocking voltage per diode	I_{RRM1}	μA	$V_{RM} = V_{RRM}$ $T_j = 25$		-	-	5.0
	I_{RRM2}		$V_{RM} = V_{RRM}$ $T_j = 150$		-	40	200
Reverse Recovery Time	T_{RR}	ns	$I_F = 0.5A$ $dI_M = 1A$ $dI_R = 0.25A$ $T_j = 25$		-	25	35
			$T_j = 25$		-	60	-
			$T_j = 125$		-	300	-
Peak recovery current	I_{RRM}	A	$T_j = 25$	$I_F = 8A$ $di/dt = -200A/\mu s$ $V_{RM} = 200V$	-	3.4	-





Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronics Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function, design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices). Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes and replaces all information previously supplied. For additional information, please visit our website <http://www.21yangjie.com> or consult your nearest Yangjie's sales office for assistance.