


1-Line, Bi-directional, Transient Voltage Suppressor



Features


- Stand-off voltage: $\pm 7V$ Max
- Transient protection for each line according to
 - IEC61000-4-2(ESD): $\sim 30kV$ (contact)
 - IEC61000-4-4 (EFT): 40A (5/50ns)
 - IEC61000-4-5(surge): 9A (8/20 μs)
- Low leakage current
- Ultra-low capacitance: $C_J = 20pF$ typ
- Low clamping voltage:
 $V_{CL} = 9.6V$ typ. @ $I_{PP} = 16A$ (TLP)
- RoHS Compliant

Applications


- Cellular Handsets
- Tablets
- Laptops
- Other portable devices
- Network communication devices

Mechanical Data

- Package: DFN1006-2L
- Case Material: "Green" Molding Compound
- Moisture Sensitivity: Level 3 per J-STD-020
- Marking Information: See Below



Definitions of electrical characteristics





γ Characteristics (Typical)






Fig.7 ESD clamping




(+8kV contact discharge per IEC61000-4-2)

Fig.8 ESD clamping t




(-8kV contact discharge per IEC61000-4-2)

Fig.9 TLP Measurement




Outline Dimensions



A	0.340	0.450	0.530
A1	0.000	0.020	0.050
A3	0.125 Ref.		
D	0.950	1.000	1.080
E	0.550	0.600	0.680
b	0.200	0.250	0.300
L	0.450	0.500	0.550
e	0.650 BSC		

Recommended PCB Layout



Unit:mm

Notes:

This recommended land pattern is for reference purposes only. Please consult your manufacturing group to ensure your PCB design guidelines are met.



Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.