



Ultra-Fast Recovery Diodes 8A FRED



Features

- Adopt FRED chip
- Low forward Voltage drop
- Fast reverse recovery time
- High frequency operation
- High purity, high temperature epoxy encapsulation for enhanced mechanical strength and moisture resistance
- Guard ring for enhanced ruggedness and long term reliability

Typical Applications

Typical applications are in switching power supplies, converters, freewheeling diodes, and reverse battery protection.

Mechanical Data

- **Package:** ITO-220AC
Molding compound meets UL 94 V-0 flammability rating, RoHS-compliant
- **Terminals** 1 T

MUR860FL (FIG.1)

IO

A

Surge(Non-repetitive)Forward Current @60Hz half sine-wave, 1 cycle, T _J =25	I _{FSM}	A	50
Current Squared Time @1ms≤t≤8.3ms T _J =25	I ² t	A ² s	12.5
Storage Temperature	T _{stg}		-55 ~ +175
Junction Temperature	T _J		-55 ~ +175
Typical Junction capacitance @4V,1MHz	C _J	pF	42
Mounting torque @recommend torque 5kg cm	Tor	kg cm	8



■Electrical Characteristics

PARAMETER	SYMBOL	UNIT	TEST CONDITIONS	Min	
-----------	--------	------	-----------------	-----	--

FIG3: Forward Voltage





FIG.5: Diagram of circuit and Testing wave form of reverse recovery time





■Outline Dimensions

ITO-220AC		
Dim	Min	Max
A	9.8	10.2
B	2.25	2.75
C	2.95	3.45
D	14.75	15.25
E	3.5	4.1
F	0.45	0.75
G	0.45	0.75
H	13.35	14.15
I	4.97	5.23
J	4.3	4.8
K	2.5	2.74
L	2.58	2.82
M	1.03	1.43



Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf is not responsible for any damage or loss caused by the use of the product in such applications.